

BH100-02 1000/1100 VDC Fuse Holder



FEATURES:

ADLER's BH100-02 touch safe fuse holder is designed for all standard 10x38 mm PV fuses such as ADLER A73 / A83 series and other cylindrical fuse up to $\varnothing 10 \times 38$ mm, it can effectively protect 1000 VDC / 1100 VDC circuits and equipment in photovoltaic applications.

DESCRIPTION:

The BH100-02 touch safe holder is designed for 10x38 mm cylindrical fuse links, especially for use with photovoltaic equipment.

This holder has an indicator light. It will light up when the circuit is interrupted.

SPECIFICATIONS:

- Rated: 1000 VDC, 30 A / 1100 VDC, 32 A
- Rated Breaking Capacity:
30 kA at 1000 VDC / 20 kA at 1100 VDC
- Wire Range: 18-8 AWG (1.5-10 mm²)
- Max. Torque: 3.4 N.m
- Maximum Heat Dissipation: 6 W
- Operation Temperature: -40 °C to 130 °C
- Material Flammability: UL 94 V0
- Degree of protection: IP20
- Mounting: DIN Rail mounting
- Standards: UL 4248-19; EN 60947-3
- Approvals: UL (File: E486822)

DIMENSIONS (mm)

