

## BH200 / BH201 1500 VDC Fuse Holder



### FEATURES:

ADLER's BH200 and BH201 touch safe fuse holders are designed for all standard 14x51 mm PV fuses such as ADLER A74 / A84 series and other cylindrical fuse up to  $\varnothing 14 \times 51$  mm, with current ratings up to 30 A at 1500 VDC, it can effectively protect 1500 VDC circuits and equipment in photovoltaic applications.

### DESCRIPTION:

BH200 and BH201 touch safe holders are designed for 14x51 mm cylindrical fuse links, especially for use with photovoltaic equipment. BH201 touch safe holder has an indicator light. It will light up when the circuit is interrupted.

### SPECIFICATIONS:

- Rated Voltage: 1500 VDC
- Rated Current: 30 A
- Rated Breaking Capacity: 10 kA
- Wire Range: 13-5 AWG (2-20 mm<sup>2</sup>)
- Max. Torque: 3.4 N.m
- Maximum Heat Dissipation: 8 W
- Operation Temperature: -40 °C to 150 °C
- Material Flammability: UL 94 V0
- Mounting: DIN Rail mounting
- Standards: UL 4248-19; EN 60947-3
- Approvals: UL (File: E486822)  
TUV (File: R50393975)

### DIMENSIONS (mm)

