

BH300 1500 VDC Fuse Holder



FEATURES:

ADLER's BH300 touch safe fuse holder is designed for all standard 10x85 mm PV fuses such as ADLER A75 / A85 series and other cylindrical fuse up to $\varnothing 10 \times 85$ mm, with current ratings up to 30 A at 1500 VDC, it can effectively protect 1500 VDC circuits and equipment in photovoltaic applications.

DESCRIPTION:

The BH300 touch safe holder is designed for 10x85 mm cylindrical fuse links, especially for use with photovoltaic equipment.

SPECIFICATIONS:

- Rated Voltage: 1500 VDC
- Rated Current: 30 A
- Rated Breaking Capacity: 30 kA
- Wire Range: 14-6 AWG (2-10 mm²)
- Max. Torque: 3.4 N.m
- Maximum Heat Dissipation: 8 W
- Operation Temperature: -40 °C to 150 °C
- Material Flammability: UL 94 V0
- Mounting: DIN Rail mounting
- Standards: UL 4248-19; EN 60947-3
- Approvals: UL (File: E486822)
TUV (File: R50394043)

DIMENSIONS (mm)

